

RETURN LOSS (dB)	TRANS. LOSS (dB)	POWER TRANS. (%)	POWER REFL. (%)	VOLT. REFL. COEFF.	VSWR
0	∞	0.00	100.00	1.00	∞
1	0.00	20.57	79.43	0.89	17.39
2	4.33	36.90	63.10	0.79	8.72
3	3.02	49.88	50.12	0.71	5.85
4	2.20	60.19	39.81	0.63	4.42
5	1.65	68.38	31.62	0.56	3.57
6	1.26	74.88	25.12	0.50	3.01
7	0.97	80.05	19.95	0.45	2.61
8	0.75	84.15	15.85	0.40	2.32
9	0.58	87.41	12.59	0.35	2.10
10	0.46	90.00	10.00	0.32	1.92
11	0.36	92.06	7.94	0.28	1.78
12	0.28	93.69	6.31	0.25	1.67
13	0.22	94.99	5.01	0.22	1.58
14	0.18	96.02	3.98	0.20	1.50
15	0.14	96.84	3.16	0.18	1.43
16	0.11	97.49	2.51	0.16	1.38
17	0.088	98.00	2.00	0.14	1.33
18	0.069	98.42	1.58	0.13	1.29
19	0.055	98.74	1.26	0.11	1.25
20	0.044	99.00	1.00	0.10	1.22
21	0.035	99.21	0.79	0.089	1.20
22	0.027	99.37	0.63	0.079	1.17
23	0.022	99.50	0.50	0.071	1.15
24	0.017	99.60	0.40	0.063	1.13
25	0.014	99.68	0.32	0.056	1.12
26	0.011	99.75	0.25	0.050	1.11
27	0.009	99.80	0.20	0.045	1.09
28	0.007	99.84	0.16	0.040	1.08
29	0.005	99.87	0.13	0.035	1.07
30	0.004	99.90	0.10	0.032	1.07
31	0.003	99.92	0.08	0.028	1.06
32	0.003	99.94	0.06	0.025	1.05
33	0.002	99.95	0.05	0.022	1.05
34	0.002	99.96	0.04	0.020	1.04
35	0.001	99.97	0.03	0.018	1.04
36	0.001	99.97	0.03	0.016	1.03
37	0.001	99.98	0.02	0.014	1.03
38	0.001	99.98	0.02	0.013	1.03
39	0.001	99.99	0.01	0.011	1.02
40	0.000	99.99	0.01	0.010	1.02